

# Prox Rex — Access Control Exit Device

## PROXIMITY REQUEST TO EXIT SWITCH

The Prox Rex is a touch sensitive wall switch, which can be used for a number of applications:

- Used in conjunction with an Access Control System to perform the function of an exit button
- Used as a remote door release switch at a reception desk etc.
- Used as a panic button that gives the user audiovisual feedback that it has been operated.
- Used to enable easy operation by the disabled.

## FEATURES

The Prox Rex unit has the following features:

- No moving parts to wear out and fail.
- 12 to 16Vdc operation.
- Only draws 50 mA at 13.6 Vdc.
- Relay output to the Access Controller, 1 Amp DC rated N/C or N/O.

The Prox Rex exit is designed primarily to be used in conjunction with an Access Control System Reader to exit a door.



# Em Rex — Emergency Exit Device

## EMERGENCY REQUEST TO EXIT SWITCH

The Em Rex is an emergency door release unit, which is used in conjunction with the Prox Rex touch to exit unit to make up a total access control exit unit.

- Used in an Access Control System to work in conjunction with an exit button to give emergency egress to comply with building codes;

## FEATURES

- Has 3x N/C-N/O outputs 1 amp DC rated;
- 1<sup>st</sup> output to the Access Controller to log the operation of the unit;
- 2<sup>nd</sup> output to break lock power directly;
- 3<sup>rd</sup> output to activate a local audio sounder (if required);
- A red indication bar also shows when the unit has been activated.

## MOUNTING

- Fits into a standard single flush box.
- Surface mounted with optional deep surround.
- Fits next to the Prox Rex on an optional special Double Flush Box (not standard) and double surround.

